



# Recommended Dimmers for Cree® A19 (75W) and A21 (100W) LED bulbs.

Cree LED bulbs are designed to be dimmed with standard incandescent type dimmers and are compatible with most Electric Low Voltage (ELV) dimmers. This list was generated from lab testing of samples and your results may vary.\*




## Works Best With

No flickering or shimmer observed and smooth dimming across range. No audible noise.

| Manufacturer | Series            | Part Number | Wall Plate Style | Load Type    | Phase Cut Edge | Rating (W) | Bulbs Per Dimmer |     |
|--------------|-------------------|-------------|------------------|--------------|----------------|------------|------------------|-----|
|              |                   |             |                  |              |                |            | min              | max |
| Leviton      | Illumatech        | IPE041      | Decorative       | ELV          | Trailing       | 300        | 1                | 7   |
| Leviton      | Illumatech        | IPL06       | Decorative       | Incandescent | Leading        | 600        | 1                | 5   |
| Leviton      | Sureslide         | 6615        | Decorative       | ELV          | Trailing       | 300        | 1                | 7   |
| Leviton      | Sureslide         | 6673        | Decorative       | CFL/LED      | Leading        | 300        | 1                | 8   |
| Lutron       | Caseta Wireless   | PD-6WCL     | Decorative       | CFL/LED      | Leading        | 600        | 1                | 8   |
| Lutron       | Diva              | DV-600P     | Decorative       | Incandescent | Leading        | 600        | 1                | 8   |
| Lutron       | Diva              | DVCL-153P   | Decorative       | CFL/LED      | Leading        | 600        | 1                | 8   |
| Lutron       | Diva              | DVELV-303P2 | Decorative       | ELV          | Trailing       | 300        | 1                | 7   |
| Lutron       | Faedra            | FAELV-500   | Traditional      | ELV          | Trailing       | 500        | 1                | 9   |
| Lutron       | Maestro           | MACL-153    | Decorative       | CFL/LED      | Leading        | 600        | 1                | 8   |
| Lutron       | RadioRA 2 Maestro | RRD-6CL     | Decorative       | LED/CFL/INC  | Leading        | 600        | 1                | 8   |
| Lutron       | Skylark           | SELV-300P   | Decorative       | ELV          | Trailing       | 300        | 1                | 7   |

## Wall Plate Style



## Works With

May produce some flicker or shimmer. Minimum adjustment to dimming level may be required. No audible noise.

| Manufacturer | Series    | Part Number | Wall Plate Style | Load Type    | Phase Cut Edge | Rating (W) | Bulbs Per Dimmer |     |
|--------------|-----------|-------------|------------------|--------------|----------------|------------|------------------|-----|
|              |           |             |                  |              |                |            | min              | max |
| Leviton      | Trimatron | 6602        | Traditional      | Incandescent | Leading        | 600        | 1                | 8   |
| Leviton      | Trimatron | 6681        | Traditional      | Incandescent | Leading        | 600        | 1                | 8   |
| Leviton      | Trimatron | 6683        | Traditional      | Incandescent | Leading        | 600        | 1                | 8   |
| Leviton      | Sureslide | 6674        | Decorative       | LED/CFL/INC  | Leading        | 600        | 1                | 8   |
| Lutron       | Skylark   | CTCL-153    | Decorative       | LED/CFL/INC  | Leading        | 600        | 1                | 8   |

## Compatible Part Numbers



### A19-75W

SA19-11027MDFD-12DE26-1-11  
SA19-11050MDFD-12DE26-1-11



### A21-100W

SA21-16027MDFD-12DE26-1-11  
SA21-16050MDFD-12DE26-1-11

\*The presence of a dimmer on this chart is not a guarantee or warranty of the compatibility of the LED bulb in any particular installation. Absence of a dimmer from this chart does not imply incompatibility.

Please reference the dimmer manufacturer's instructions for installation and further information.