



LED LIGHTING

Cree LED bulbs are designed to be dimmed with standard incandescent type dimmers and are compatible with most Electric Low Voltage (ELV) dimmers. This list was generated from lab testing of samples and your results may vary.*

Works Best With

No flickering or shimmer observed and smooth dimming across range.
No audible noise.

Manufacturer	Series	Part Number	Load Type	Phase Cut Edge	Rating (W)	Bulbs Per Dimmer	
						min	max
Leviton	Decora	DSL-06	LED/CFL/INC	Leading	600	1	20
Leviton	Decora	IPS06	Incandescent/LED	Leading	600/150	1	20
Leviton	Illumatech	IPE041	ELV	Trailing	400VA	1	25
Leviton	Illumatech	IPL06	Incandescent	Leading	600	1	20
Leviton	Sureslide	6633	Incandescent	Leading	600	1	20
Leviton	Sureslide	6672	Incandescent/LED	Leading	600/150	1	20
Leviton	Sureslide	6674	LED/CFL/Inc	Leading	600/150	1	20
Leviton	Trimatron	6602	Incandescent	Leading	600	1	20
Lutron	Caseta Wireless	PD-6WCL	CFL/LED	Leading	600	1	20
Lutron	Credenza	TTCL-100	LED	Leading	250	1	20
Lutron	Diva	DV-600P	Incandescent	Leading	600	1	20
Lutron	Diva	DVCL-153P	CFL/LED	Leading	600	1	20
Lutron	Diva	TG-600PH	Incandescent	Leading	600	1	20
Lutron	Lumea	LGCL-153	CFL/LED	Leading	600	1	20
Lutron	RadioRA2	PRD6NA	Incandescent	Leading	600	1	20
Lutron	Skylark	SELV-300P	ELV	Trailing	300	1	20
Lutron	Tabletop	TBL-03	Incandescent/LED	Leading	300/150	1	20

Works With

May produce some flicker or shimmer. Minimum adjustment to dimming level may be required.
No audible noise.

Manufacturer	Series	Part Number	Load Type	Phase Cut Edge	Rating (W)	Bulbs Per Dimmer	
						min	max
Leviton	Sureslide	6615	ELV	Trailing	300	1	20

Compatible Part Numbers



R20

TR20-09827FLFH25-12DE26-1-11
TR20-09850FLFH25-12DE26-1-11

*The presence of a dimmer on this chart is not a guarantee or warranty of the compatibility of the LED bulb in any particular installation. Absence of a dimmer from this chart does not imply incompatibility.

Please reference the dimmer manufacturer's instructions for installation and further information.